

NEOZ

LITTLE MARGARITA

CORDLESS TABLE LAMP



DESIGNED & ASSEMBLED
IN AUSTRALIA



5 YEARS
WARRANTY



95+ CRI
LED



ALL PARTS
REPLACEABLE



INTERNATIONAL
DELIVERY



Sand Blasted
Hand Blown Glass



Handling Accessory
6 Lamp Carrier
(Optional)

Neoz Cordless Lighting

Designed and made in
Sydney Australia

www.neoz.com

Contact

20 Tepko Road Terrey Hills
NSW 2084 Australia
Tel +61 2 9810 5520
Fax +61 2 9555 1054
Email sales@neoz.com.au

Service

All parts are replaceable or
recyclable.
Technical support available at
service@neoz.com.au

NEOZ Warranty


NEOZ warrants the cordless
lamp range for 5 Years
from the date of purchase.
For further information, see
www.neoz.com.au/warranty



LITTLE MARGARITA - Technical Description

The Little Margarita features a hand blown assymmetric frosted glass diffuser providing an omni directional soft ambient light.

Designer	Peter Ellis, David Skelley
Year of Design	1999
IP Rating	IP52
Dimensions	180mm x 100mm (7") x (4")
Weight	PRO - 1.11 kg / 2.5 lb ECO - 1.00 kg / 2.2 lb UNO - 0.88 kg / 1.9 lb
Approvals & Standards	CE, CSA, C-Tick, FCC, RoHS, SASO
EU Energy Regulation	Exempt - LED lamps operate on batteries



Type	Battery	Cells	Charge Time	Light Source Option	Colour Temperature (Kelvin)	Operating Time (hours)			Brightness (lumens)	CRI*	Bulb Life (Hours)
						Normal mode	High	Med			
UNO	Panasonic Li-ion 3.7V 2900mAh 500+ cycles	1	5.5hrs	1W LED Warm White (Standard)	2600k	13	35	130	68+	95+	50,000+
				1W LED Warm Candle White*	1800k	13	35	130	58+	93+	50,000+
ECO	Panasonic Li-ion 3.7V 2900mAh 500+ cycles	3	4.5hrs	1W LED Warm White (Standard)	2600k	30	54	130	85+	95+	50,000+
				1W LED Warm Candle White*	1800k	30	54	130	75+	93+	50,000+
PRO	Panasonic Li-ion 11.1V 5800mAh 500+ cycles	6	8.5hrs	1W LED Warm White (Standard)	2600k	66	116	310	85+	95+	50,000+
				1W LED Warm Candle White*	1800k	66	116	310	75+	93+	50,000+

COLOUR RENDERING INDEX (CRI) The quantitative measure of the ability of a light source to reproduce the colors of various objects faithfully in comparison with an ideal or natural light source. The highest possible CRI is 100.

POWER SOURCE 100 - 240V Switch-Mode Electronic Power Supply
Approved for worldwide usage supplied with appropriate mains electric plug type



Single Base Station 1 Lamp	Small Recharging Tray 4 Lamps	Large Recharging Tray 12 Lamps	Small Recharging Station 24 Lamps	Medium Recharging Station 36 Lamps	Large Recharging Station 48 Lamps
--------------------------------------	---	--	---	--	---